



Specs & Techs  
03/2023



# Auddy



design by  
Bruno Van Meenen





Audy-In white with honeycomb

# Audy-In

design by  
Bruno Van Meenen




Audy-In gunmetal



Audy-In brass with honeycomb



FALSE & CONCRETE ceiling



# Audy-In

350mA - **required remote mounted driver see below**

1 x LED array 6.25W **(LED incl.)** - 350mA - 2700K (633lm) or 3000K (673lm) - CRI >95

**FALSE ceiling** = aperture : Ø 47 - depth : min. 50 mm - depth for driver in false ceiling : min. 70 mm

**CONCRETE ceiling** = aperture : Ø 47 - depth : min. 50 mm - depth for driver in concrete ceiling : min. 110 mm

CEILING -

◆ Choose beam:  
M=medium 23°  
or W=wide 40°

COLOR LED		FRAME brass	FRAME black	FRAME white	FRAME gunmetal	FRAME bronze	FRAME nickel
2700K		AUDY 1273◆	AUDY 1272◆	AUDY 1271◆			
2700K					AUDY 1274◆	AUDY 1277◆	AUDY 1279◆
3000K		AUDY 1303◆	AUDY 1302◆	AUDY 1301◆			
3000K					AUDY 1304◆	AUDY 1307◆	AUDY 1309◆
+ honeycomb	2700K	AUDY 1273H◆	AUDY 1272H◆	AUDY 1271H◆			
+ honeycomb	2700K				AUDY 1274H◆	AUDY 1277H◆	AUDY 1279H◆
+ honeycomb	3000K	AUDY 1303H◆	AUDY 1302H◆	AUDY 1301H◆			
+ honeycomb	3000K				AUDY 1304H◆	AUDY 1307H◆	AUDY 1309H◆

## REQUIRED REMOTE MOUNTED DRIVER

DEVICE	DIM.
1 x	LC (TRIAC/IGBT)
2 x	LC (TRIAC/IGBT)
1-2 x	PU (PUSH-DIM) + DA (DALI)
1-2 x	DA (DALI)
1-2 x	DA (DALI)
2-6 x	PU (PUSH-DIM) + DA (DALI) + 1-10 (1-10V)

### DRIVER


D 6WT
D 18WT
D 15WP*
D 15WDA EU
D 15WDA US*
D 40WDP*

For warranty use only Trizo21® supplied LED drivers as mentioned.  
For all specs and techs about drivers, see [www.trizo21.com/drivers](http://www.trizo21.com/drivers)

driver remote mounting: driver does not fit through cutout hole of fixture  
\*110V-230V



FALSE & CONCRETE ceiling



# Audy-In OUT

350mA - **required remote mounted driver see below**

1 x LED array 6,25W (incl.) - 350mA - 2700K (633lm) or 3000K (673lm) - 3000K - CRI >95

FALSE ceiling = aperture : Ø 47 - depth : min. 50 mm - depth for driver in false ceiling : min. 70 mm

CONCRETE ceiling = aperture : Ø 47 - depth : min. 50 mm - depth for driver in concrete ceiling : min. 110 mm

CEILING -

◆ Choose beam:  
M=medium 23°  
or W=wide 40°

COLOR LED	FRAME black	FRAME white
2700K	AUDEX 1272◆	AUDEX 1271◆
3000K	AUDEX 1302◆	AUDEX 1301◆

## REQUIRED REMOTE MOUNTED DRIVER

DEVICE	DIM.
1 x	LC (TRIAC/IGBT)
2 x	LC (TRIAC/IGBT)
1-2 x	PU (PUSH-DIM) + DA (DALI)
1-2 x	DA (DALI)
1-2 x	DA (DALI)
2-6 x	PU (PUSH-DIM) + DA (DALI) + I10 (1-10V)

### DRIVER

D 6WT
D 18WT
D 15WP*
D 15WDA EU
D 15WDA US*
D 40WDP*

For warranty use only Trizo21® supplied LED drivers as mentioned.  
For all specs and techs about drivers, see [www.trizo21.com/drivers](http://www.trizo21.com/drivers)

driver remote mounting: driver does not fit through cutout hole of fixture  
\*110V-230V



FALSE & CONCRETE ceiling



◆ Choose beam:  
M=medium 23°  
or W=wide 40°

# Audy-In BATHROOM

350mA - **required remote mounted driver see below**

1 x LED array 6,25W (incl.) - 350mA - 2700K (633lm) or 3000K (673lm) - 3000K - CRI >95

FALSE ceiling = aperture : Ø 47 - depth : min. 50 mm - depth for driver in false ceiling : min. 70 mm

CONCRETE ceiling = aperture : Ø 47 - depth : min. 50 mm - depth for driver in concrete ceiling : min. 110 mm

CEILING -

COLOR LED	FRAME brass	FRAME black	FRAME white	FRAME gunmetal	FRAME bronze	FRAME nickel
2700K	AUDEX 1273◆	AUDEX 1272◆	AUDEX 1271◆			
2700K				AUDEX 1274◆	AUDEX 1277◆	AUDEX 1279◆
3000K	AUDEX 1303◆	AUDEX 1302◆	AUDEX 1301◆			
3000K				AUDEX 1304◆	AUDEX 1307◆	AUDEX 1309◆

## REQUIRED REMOTE MOUNTED DRIVER

DEVICE	DIM.
1 x	LC (TRIAC/IGBT)
2 x	LC (TRIAC/IGBT)
1-2 x	PU (PUSH-DIM) + DA (DALI)
1-2 x	DA (DALI)
1-2 x	DA (DALI)
2-6 x	PU (PUSH-DIM) + DA (DALI) + 1-10 (1-10V)

### DRIVER

D 6WT
D 18WT
D 15WP*
D 15WDA EU
D 15WDA US*
D 40WDP*

For warranty use only Trizo21® supplied LED drivers as mentioned.  
For all specs and techs about drivers, see [www.trizo21.com/drivers](http://www.trizo21.com/drivers)

driver remote mounting: driver does not fit through cutout hole of fixture  
\*110V-230V

Kerrebroek 52 | B-9850 Deinze | Belgium | +32 (0)9 380 43 43

[info@trizo21.com](mailto:info@trizo21.com) | [www.trizo21.com](http://www.trizo21.com) | © Trizo21